

## SSCP2907AGS7

## **PNP Switching Transistor**

### Features

VCB	VCE	VEB	IC
-60V	-60V	-5V	-600mA

### Description

This product is general usage and suitable for many different applications. It can be used for medium power amplifiers and switches requiring collector currents up to 500 mA.


## Applications

- Low current and high precision circuits such preamplifiers, oscillators, current mirror configuration
- Medium power amplification and switching


## Ordering Information

Device	Package	Shipping	
SSCP2907AGS7	SOT-323	3000/Reel	


## Pin configuration



SOT-323



**Circuit Diagram** 



Marking(Top View)



2/5



## ightharpoonup Absolute Maximum Ratings(T<sub>A</sub>=25°C unless otherwise noted)


Parameter	Symbol	Value	Unit
Collector-Base Voltage	V <sub>CBO</sub>	-60	V
Collector- Emitter Voltage	V <sub>CEO</sub> -60		V
Emitter-Base Voltage	V <sub>EBO</sub> -5		V
Collector Current-Continuous	Ic	-600	mA
Collector Power Dissipation	Pc	225	mW
Junction Temperature	TJ	150	$^{\circ}$
Storage Temperature	T <sub>STG</sub>	-55 to 150	$^{\circ}$


## ➤ Electrical Characteristics (T<sub>A</sub>=25°C unless otherwise noted)

Parameter	Symbol	Test Conditions	Min.	Тур.	Max.	Unit
Collector-Base Breakdown Voltage	ВУсво	I <sub>C</sub> =-100uA,I <sub>E</sub> =0	-60			V
Collector-emitter Breakdown Voltage	BV <sub>CEO</sub>	I <sub>C</sub> =-1mA,I <sub>B</sub> =0	-60			V
Emitter -Base Breakdown Voltage	BV <sub>EBO</sub>	I <sub>E</sub> =-100uA,I <sub>C</sub> =0	-5			V
Collector Cutoff Current	I <sub>CBX</sub>	V <sub>CE</sub> =-30V, V <sub>EB</sub> =-0.5V,			-50	nA
Collector Cutoff Current	I <sub>CBO</sub>	V <sub>CB</sub> =-50V,I <sub>E</sub> =0			-20	nA
Emitter Cutoff Current	I <sub>EBO</sub>	V <sub>EB</sub> =-3V,I <sub>C</sub> =0			-10	nA
	h <sub>FE1</sub>	V <sub>CE</sub> =-10V,I <sub>C</sub> =-150mA	100		300	
DC Current Gain	h <sub>FE2</sub>	V <sub>CE</sub> =-10V,I <sub>C</sub> =-0.1mA	75			
	h <sub>FE3</sub>	V <sub>CE</sub> =-10V,I <sub>C</sub> =-500mA	50			
Collector-Emitter Saturation Voltage	V <sub>CE(sat)</sub>	I <sub>C</sub> =-500mA,I <sub>B</sub> =-50mA			-1.6	V
Base-Emitter Saturation Voltage	V <sub>BE(sat)</sub>	I <sub>C</sub> =-500mA,I <sub>B</sub> =-50mA			-2.6	V
Transition fragues av	f⊤	V <sub>CE</sub> =-20V,I <sub>C</sub> =-50mA	250	250		MHz
Transition frequency		f=100MHz	250			
Dolov Time	ta	V <sub>CC</sub> =-30V,I <sub>C</sub> =-150mA,			40	
Delay Time		I <sub>B1</sub> =-15mA		10	ns	
Rise Time	t <sub>r</sub>	Vcc=-30V,Ic=-150mA,			25	ns
Rise Time		I <sub>B1</sub> =-15mA				
Storage Time	ts	V <sub>CC</sub> =-6V,I <sub>C</sub> =-150mA,			225	ns
Storage Time		I <sub>B1</sub> = -I <sub>B2</sub> =-15mA				
Fall Time	+-	V <sub>CC</sub> =-6V,I <sub>C</sub> =-150mA,		60	60	ns
rali ililie	t <sub>f</sub>	I <sub>B1</sub> =-I <sub>B2</sub> =-15mA			00	



# $\succ$ Typical Performance Characteristics (T<sub>A</sub>=25 $^{\circ}$ C unless otherwise noted)





### Collector Current vs. Base-Emitter Voltage

1.2 Passe-Emitter Saturation

Noltage Versation

1.2 T<sub>A=25°C</sub>

Noltage Versation

1.2 T<sub>A=100°C</sub>

1.2 T<sub>A=100°C</sub>

1.3 T<sub>A=100°C</sub>

1.4 T<sub>A=100°C</sub>

1.5 T<sub>A=100°C</sub>

1.6 T<sub>A=100°C</sub>


1.7 T<sub>A=100°C</sub>

1.7 T<sub>A=100°C</sub>

1.8 T<sub>A=100°C</sub>


1.9 T<sub>A=100°C</sub>

DC Current Gain vs. Collector Current



V<sub>BE(sat)</sub> vs. Collector Current

Collector Current\_I<sub>c</sub>(-mA)





V<sub>CE(sat)</sub> vs. Collector Current


### Power derating vs. Ambient temperature



# Package Information







Symbol	Dimensions In Millimeters		Dimensions In Inches		
	Min.	Max.	Min.	Max.	
Α	0.900	1.100	0.035	0.043	
A1	0.000	0.100	0.000	0.004	
A2	0.900	1.000	0.035	0.039	
b	0.200	0.400	0.008	0.016	
С	0.080	0.150	0.003	0.006	
D	2.000	2.200	0.079	0.087	
E	2.150	2.450	0.085	0.096	
E1	1.150	1.350	0.045	0.053	
е	0.650 TYP.		0.026 TYP.		
e1	1.200	1.400	0.047	0.055	
L	0.260	0.460	0.010	0.018	
L1	0.525 REF.		0.021 REF.		
θ	0°	8°	0°	8°	



#### **DISCLAIMER**

SSCSEMI RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. SSCSEMI DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICIENCE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

THE GRAPHS PROVIDED IN THIS DOCUMENT ARE STATISTICAL SUMMARIES BASED ON A LIMITED NUMBER OF SAMPLES AND ARE PROVIDED FOR INFORMATIONAL PURPOSE ONLY. THE PERFORMANCE CHARACTERISTICS LISTED IN THEM ARE NOT TESTED OR GUARANTEED. IN SOME GRAPHS, THE DATA PRESENTED MAY BE OUTSIDE THE SPECIFIED OPERATING RANGE (E.G,. OUTSIDE SPECIFIED POWER SUPPLY RANGE ) AND THEREFORE OUTSIDE THE WARRANTED RANGE.

OUR PRODUCT SPECIFICATIONS ARE ONLY VALID IF OBTAINED THROUGH THE COMPANY'S OFFICIAL WEBSITE, CRM SYSTEM, OR OUR SALES PERSONNEL CHANNELS. IF CHANGES OR SPECIAL VERSIONS ARE INVOLVED, THEY MUST BE STAMPED WITH A QUALITY SEAL AND MARKED WITH A SPECIAL VERSION NUMBER TO BE VALID.